

## Zapper STB Reset Instructions

1. Press the **"MENU"** key and using the arrow keys, highlight **"Installation"** (top menu item) and press the **"OK"** key. then enter the password **" 0 0 0 0 "**
2. Select the **"3"** menu item (**Reset Factory Defaults**) by either highlighting it and pressing the **"OK"** key or pressing the number **"3"** key.

Once inside make sure that it says, **"Reset Type ALL"** and press the **"OK"** key.

It will bring up a screen that says, **"This will make STB factory default status. Do you want to proceed?"**. Using the right or left arrow keys make the **"YES"** yellow and press the **"OK"** key.

3. The Zapper will reboot and when it comes up with a world picture and a selection - make sure **"English"** is yellow and press the **"OK"** key.

The channels will scan into the STB and the progress bar on the bottom will tell you the progress. When completed, you want to make sure that you **"SAVE CHANGES"** by pressing the **"OK"** key. If you do not you will have to repeat procedure. Enjoy!

=====

## HD STB Reset Procedure

1. Press the **"MENU"** key and use the arrows to go to the **"System Information"** tab (right hand side of menu bar), make sure that **"Factory Reset"** is highlighted and press the **"OK"** button.

Use the right or left arrow key to change option to **"Yes"** and use the down arrow to highlight **"Start"** and press the **"OK"** key.

2. When a box boots it will come up with the installation menu, press the **"EXIT"** button **3 times** until you get to the **"MANUAL SEARCH"** screen.

Use the down arrow to highlight **"Start Search"** and press the **"OK"** button.

The box will scan all the channels and ask you to **"Save Changes"** press the **"OK"** button.

3. Press the **"EXIT"** button and enjoy!